

IN THE CLAIMS:

Please cancel claims 1-5 and 8-12 without prejudice, and amend the claims as follows:

Claims 1-12. (Cancelled).

13. (Previously presented) An optical time domain multiplexer system, comprising:
an optical multiplexer with at least one optical data access, an optical probe access and an optical data output and including a semiconductor optical amplifier Mach-Zehnder interferometer having:
a first set of at least three semiconductor optical amplifiers configured to receive n different interleaved wavelength channels, each at a bit-rate F/n , and an optical clock signal, having a frequency F and a wavelength λ_c ,
a second set of at least two semiconductor optical amplifiers, wherein the first set and the second set are in series with one another, and
a third set of at least one semiconductor optical amplifier configured to output a converted optical time domain multiplexed signal at a bit-rate of F and at a wavelength of λ_c , wherein the second set and the third set are in series with one another,
wherein an optical data signal carried by the n different interleaved wavelength channels and the optical clock signal are launched respectively on said at least one optical data access and said optical probe access such that in said optical multiplexer said optical data signal is synchronized with said optical clock signal to produce the converted optical time domain multiplexed signal on said optical data output.
14. (Previously presented) The optical time domain multiplexer system of claim 13, further comprising an optical filter on said optical data output and configured to pass only the converted optical time domain multiplexed signal at a wavelength of λ_c .
15. (Previously presented) The optical time domain multiplexer system of claim 13, further comprising an optical clock that includes a multiplier and a laser and configured to receive a clock signal at a frequency F/n and generate said optical clock signal at frequency F .

16. (Previously presented) The optical time domain multiplexer system of claim 15, wherein the multiplier is configured to run an integrated electro-absorption modulator in combination with the laser.
17. (Previously presented) The optical time domain multiplexer system of claim 16, wherein the integrated electro-absorption modulator is a LiNbO₃ Mach-Zehnder intensity modulator.
18. (Previously presented) The optical time domain multiplexer system of 16, wherein the laser is a distributed feedback laser.
19. (Previously presented) The optical time domain multiplexer system of claim 15, further comprising an emitter configured to generate the clock signal at a frequency F/n received by the optical clock.
20. (Previously presented) The optical time domain multiplexer system of claim 13, wherein the optical multiplexer includes a first optical data access and a second optical data access, and the n different interleaved wavelength channels are launched in parallel on both the first and the second optical data access.

Please add the following new claim 21:

21. (New) An optical module comprising:
an optical multiplexer with at least one optical data access, an optical probe access and an optical data output, wherein an optical data signal carried by n different interleaved wavelength channels, each at a bit-rate F/n , as well as an optical clock signal at frequency F and at a wavelength λ_c are launched respectively on said at least one optical data access and said optical probe access such that in said optical multiplexer said optical data signal is synchronized with said optical clock signal to give a converted optical time domain multiplexed signal on said optical data output at a bit-rate of F and at a wavelength of λ_c ; and
an optical clock that includes a multiplier and a laser and configured to receive a clock signal at a frequency F/n and generate said optical clock signal at frequency F , wherein said optical multiplexer includes a semiconductor optical amplifier Mach-Zehnder interferometer, comprising:

a first set of at least three semiconductor optical amplifiers configured to receive the n different interleaved wavelength channels and said optical clock signal;

a second set of at least two semiconductor optical amplifiers, wherein the first set and the second set are in series with one another; and

a third set of at least one semiconductor optical amplifier configured to output the converted optical time domain multiplexed signal at a bit-rate of F and at a wavelength of λ_c , wherein the second set and the third set are in series with one another.